

# of Poles	Over-all * A No Cover	Over-all * A w/Cover	Mntg Ear B No Cover	Mntg Ear B w/Cover	Switches C No Cover	Switches E & C w/Cover	Cover D	Mount Rod F No Cover	Mount Rod F w/Cover
	* Add 1/8 inch if DIN Rail								
1	1 9/16	1 11/16	1 3/16	1 5/16	11/16	13/16	1 7/8	1 1/4	1 3/8
2	2 3/16	2 5/16	1 13/16	1 15/16	1 5/16	1 7/16	2 1/2	1 7/8	2
3	2 13/16	2 15/16	2 7/16	2 9/16	1 15/16	2 1/16	3 1/8	2 1/2	2 5/8
4	3 7/16	3 9/16	3 1/16	3 3/16	2 9/16	2 11/16	3 3/4	3 1/8	3 1/4
5	4 1/16	4 3/16	3 11/16	3 13/16	3 3/16	3 5/16	4 3/8	3 3/4	3 7/8
6	4 11/16	4 13/16	4 5/16	4 7/16	3 13/16	3 15/16	5	4 3/8	4 1/2
7	5 5/16	5 7/16	4 15/16	5 1/16	4 7/16	4 9/16	5 5/8	5	5 1/8
8	5 15/16	6 1/16	5 9/16	5 11/16	5 1/16	5 3/16	6 1/4	5 5/8	5 3/4
9	6 9/16	6 11/16	6 3/16	6 5/16	5 11/16	5 13/16	6 7/8	6 1/4	6 3/8
10	7 3/16	7 5/16	6 13/16	6 15/16	6 5/16	6 7/16	7 1/2	6 7/8	7
11	7 13/16	7 15/16	7 7/16	7 9/16	6 15/16	7 1/16	8 1/8	7 1/2	7 5/8
12	8 7/16	8 9/16	8 1/16	8 3/16	7 9/16	7 11/16	8 3/4	8 1/8	8 1/4
13	9 1/16	9 3/16	8 11/16	8 13/16	8 3/16	8 5/16	9 3/8	8 3/4	8 7/8
14	9 11/16	9 13/16	9 5/16	9 7/16	8 13/16	8 15/16	10	9 3/8	9 1/2
15	10 5/16	10 7/16	9 15/16	10 1/16	9 7/16	9 9/16	10 5/8	10	10 1/8
16	10 15/16	11 1/16	10 9/16	10 11/16	10 1/16	10 3/16	11 1/4	10 5/8	10 3/4
17	11 9/16	11 11/16	11 3/16	11 5/16	10 11/16	10 13/16	11 7/8	11 1/4	11 3/8
18	12 3/16	12 5/16	11 13/16	11 15/16	11 5/16	11 7/16	12 1/2	11 7/8	12
19	12 13/16	12 15/16	12 7/16	12 9/16	11 15/16	12 1/16	13 1/8	12 1/2	12 5/8
20	13 7/16	13 9/16	13 1/16	13 3/16	12 9/16	12 11/16	13 3/4	13 1/8	13 1/4
21	14 1/16	14 3/16	13 11/16	13 13/16	13 3/16	13 5/16	14 3/8	13 3/4	13 7/8
22	14 11/16	14 13/16	14 5/16	14 7/16	13 13/16	13 15/16	15	14 3/8	14 1/2
23	15 5/16	15 7/16	14 15/16	15 1/16	14 7/16	14 9/16	15 5/8	15	15 1/8
24	15 15/16	16 1/16	15 9/16	15 11/16	15 1/16	15 3/16	16 1/4	15 5/8	15 3/4
25	16 9/16	16 11/16	16 3/16	16 5/16	15 11/16	15 13/16	16 7/8	16 1/4	16 3/8
26	17 13/16	17 15/16	17 7/16	17 9/16	16 15/16	17 1/16	18 1/8	17 1/2	17 5/8
27	18 7/16	18 9/16	18 1/16	18 3/16	17 9/16	17 11/16	18 3/4	18 1/8	18 1/4
28	19 1/16	19 3/16	18 11/16	18 13/16	18 3/16	18 5/16	19 3/8	18 3/4	18 7/8
29	19 11/16	19 13/16	19 5/16	19 7/16	18 13/16	18 15/16	20	19 3/8	19 1/2
30	20 5/16	20 7/16	19 15/16	20 1/16	19 7/16	19 9/16	20 5/8	20	20 1/8
31	20 15/16	21 1/16	20 9/16	20 11/16	20 1/16	20 3/16	21 1/4	20 5/8	20 3/4
32	21 9/16	21 11/16	21 3/16	21 5/16	20 11/16	20 13/16	21 7/8	21 1/4	21 3/8
33	22 3/16	22 5/16	21 13/16	21 15/16	21 5/16	21 7/16	22 1/2	21 7/8	22
34	22 13/16	22 15/16	22 7/16	22 9/16	21 15/16	22 1/16	23 1/8	22 1/2	22 5/8
35	23 7/16	23 9/16	23 1/16	23 3/16	22 9/16	22 11/16	23 3/4	23 1/8	23 1/4
36	24 1/16	24 3/16	23 11/16	23 13/16	23 3/16	23 5/16	24 3/8	23 3/4	23 7/8
37	24 11/16	24 13/16	24 5/16	24 7/16	23 13/16	23 15/16	25	24 3/8	24 1/2
38	25 5/16	25 7/16	24 15/16	25 1/16	24 7/16	24 9/16	25 5/8	25	25 1/8
39	25 15/16	26 1/16	25 9/16	25 11/16	25 1/16	25 3/16	26 1/4	25 5/8	25 3/4
40	26 9/16	26 11/16	26 3/16	26 5/16	25 11/16	25 13/16	26 7/8	26 1/4	26 3/8
41	27 3/16	27 5/16	26 13/16	26 15/16	26 5/16	26 7/16	27 1/2	26 7/8	27
42	27 13/16	27 15/16	27 7/16	27 9/16	26 15/16	27 1/16	28 1/8	27 1/2	27 5/8
43	28 7/16	28 9/16	28 1/16	28 3/16	27 9/16	27 11/16	28 3/4	28 1/8	28 1/4
44	29 1/16	29 3/16	28 11/16	28 13/16	28 3/16	28 5/16	29 3/8	28 3/4	28 7/8
45	29 11/16	29 13/16	29 5/16	29 7/16	28 13/16	28 15/16	30	29 3/8	29 1/2
46	30 5/16	30 7/16	29 15/16	30 1/16	29 7/16	29 9/16	30 5/8	30	30 1/8
47	30 15/16	31 1/16	30 9/16	30 11/16	30 1/16	30 3/16	31 1/4	30 5/8	30 3/4
48	31 9/16	31 11/16	31 3/16	31 5/16	30 11/16	30 13/16	31 7/8	31 1/4	31 3/8
49	32 3/16	32 5/16	31 13/16	31 15/16	31 5/16	31 7/16	32 1/2	31 7/8	32
50	32 13/16	32 15/16	32 7/16	32 9/16	31 15/16	32 1/16	33 1/8	32 1/2	32 5/8
51	34 1/16	34 3/16	33 11/16	33 13/16	33 3/16	33 5/16	34 3/8	33 3/4	33 7/8
52	34 11/16	34 13/16	34 5/16	34 7/16	33 13/16	33 15/16	35	34 3/8	34 1/2

Dimension Code:

- A = Width of Switch Block overall, including Mounting Ears
- B = Distance between centers of Mounting Ear slots
- C = Width of Switch Block with Barriers (including Barriers automatically provided at each end of Switch Block, but not including Mounting Ears)
- D = Width of Cover
- E = Width of recommended panel cutout for Back-Connected Switch Blocks
- F = Length of Mounting Rod

Dimension Equations: (In inches)

- C without Cover = (Number of poles * 5/8) + 1/16 [see Note]
- C with Cover or Back-Connected = (Number of poles * 5/8) + 3/16 [see Note]
- A = C + 7/8 [and Add 1/8 inch if DIN Rail mounted]
- B = C + 1 1/2
- E = C
- D = C + (1+1/16)
- F = C + 9/16

Note - To allow for extra mounting support, for 26-50 poles 5/8 inch is added to **C**; for 51 or more poles, 1 1/4 inches are added to **C**. The Mounting Dimensions Table above includes this addition.